



Model Number: 20211127

Clean Storm 1500 psi 3 Gpm Cold Pressure Washing Cart 20211127 230 volt single Phase GTIN NA

Manufacturer: Clean Storm

Clean Storm 1500 psi 3 Gpm Cold Pressure Washing Cart 20211127

The carted cold water, electric powered pressure washers use a heavy tube steel frame protected by an industrial coating. This frame style offers excellent portability and is equipped with two " tires. 1000 psi pressure washer features include an industrial motor that is totally enclosed and thermal overload protected, industrial triplex plunger pump with ceramic plungers and stainless steel valves is protected by unloader valve. This 2 gpm pressure washer is equipped with low pressure chemical injection for application of concentrate liquid detergents and is activated by a hi-low pressure adjustable nozzle on the trigger gun.

Brand: Clean Storm

Water Type: Cold

Powered By: Electric Motor

Mounting Type: Cart

Flow Rate in GPM / LPM: 3 / 11.4

Horsepower: 3

Product Dimensions: 30" x 21.5" x 36"

Voltage / Amperage / Phase: 230-240 Volt / 16 amp run - 20 Amp surge / 1 phase

NEMA 6-20 Plug

Pump Thermal Protection: Mechanical 140° F with 1/4" barbed connection for adding additional tubing when used indoors.

Max Pump Inlet Water Temp: 140° F

Hose Dimension: 50' x 3/8"

Power Cord: 35' with GFCI NEMA 6-20 Plug

Ship Weight: 165

Operating Pressure in PSI / Bar: 1500 / 103.5

Wand and hose rack are integrated into frame design

Three Gallon plastic chemical tank

Amp draw is based on water pressure. Pump needs 8 amps to turn on and 8 amps to push to 1500 psi.

Each 187.5 psi will create 1 amp draw above the 8 amps to turn on.

Example to set to 500 psi uses 2.67 amp + 8 to turn on = 10.67 total amps.

1000 psi = 5.33 for pressure + 8 amps to turn on = 13.33 amps

1100 psi = 5.87 amp + 8 amps to turn on = 13.86 amps

Equipment: Carpet Cleaning Machines > Vacuum Cleaners > HEPA Concrete Dust Slurry Hazmat Vacuums >

1200 psi = 6.4 amps + 8 amps to turn on = 14.4 amps

This is important to know if I am using the option splitter box below and dual 15 amp breakers.

If the option splitter box is on dual 20 amp 120 volt breakers, you can operate the pressure washer and full capacity.

Optional:

Can operate on 2 standard 120 volt wall outlets

Power Joiner Step Up Inverter Electric AC Converts Dual 20 amp 115 Volt outlets to 240 Volt 3 wire 20 amp Use [Reverse6-20R] Level 2

Availability: This product was added to our catalog on Wednesday 24 November, 2021